



Directional Power Sensor

5010B, 5014



The RF Experts

The Bird Directional Power Sensor (DPS) is the most flexible RF sensor on the market today. With this Dual-Socket, Thruline® sensor, you may select from a wide range of Bird Elements to tailor the unit to your needs over a wide range of frequencies and power levels. Also, select field changeable input and output RF connectors from dozens of types including (N, BNC, HN, 7/16 DIN). Operate your sensor with either our new hand held display, the 5000-XT, via a computer with our windows compatible software tool the VPM3, or with our Andriod RF Meter App.

The DPS measures True Average Power and/or Peak Power with exceptional accuracy that is traceable to National Institute of Standards and Technology (NIST). It is also a highly economical RF power measurement tool offering reliable results for hundreds, not thousands of dollars.

PROBLEMS • SOLUTIONS

Downtime is necessary

- Monitor and perform maintenance for monitoring while DUT is in-service.
- Measure forward and reflected power to troubleshoot system failures.

Over-spending on unneeded functionality.

- Interchangeable sensing elements.
- USB connectivity, no meter required.
- Complimentary Virtual Power Meter (VPM3) software.

Varying field tech skill levels.

- Sensor plugs and plays with 5000-XT meter.

Need greater confidence in measurement.

- No field calibration required.
- NIST traceable calibration.

APPLICATIONS

DPS measures: True average power, peak power.

Measurements performed: Standard elements; true average forward power, true average reflected power, Peak detecting elements; peak forward power.

Calculations performed: VSWR, Return loss, Reflection Coefficient.

Directional Power Sensor

5010B, 5014

DPS SPECIFICATIONS

Frequency Range	Element dependent, 2 MHz to 2.7 GHz
Power Range	Element dependent, 125 mW to 1 kW full
Impedance	50 Ohms
Peak/Average Ratio	10 dB maximum with DPM elements
Accuracy	True Average Power, $\pm 5\%$ of reading (15 °C to 35°C), $\pm 7\%$ of reading (-10 °C to 50°C), Peak Power, $\pm 8\%$ of full scale
Insertion VSWR	1.05:1 from 0.45 to 1000 MHz (with N connectors)
Settling Time	<2.5 seconds
Connector(s)	QC Type. Female N normally supplied
Power Supply	From host instrument via cable connection
Interface(s)	5010B DB9 (Proprietary Configuration) 5014 USB 1.1 Type B
Weight	1.12 lbs (0.51 kg)
Dimensions HxWxD [inches (mm)]	2.3" H x 2.1" W x 3.5" D (58 mm x 53mm x 89 mm) excluding connectors
Directivity	30 dB typical (exact value depends on element selected)
Humidity, Max.	95% maximum (non-condensing)
Pulse width Parameters	>100 MHz 800 ns minimum; 26-99 MHz 1.5 μ s minimum; 2-25 MHz 15 μ s minimum;
Pulse Rep. Rate Peak	15 pps minimum
Pulse Duty Factor	1 x 10 ⁻⁴ minimum
Dynamic Range	16 dB
Operating Temp [°C (°F)]	-10 to +50 (14° to 122°)
Storage Temp [°C (°F)]	-40 to +75 (-40° to 167°)

ACCESSORIES

5A2653-6L2	USB Locking Cable 6'
5A2653-10	USB Cable 10'
5A2264-09-MF-10	DB9 Cable 10'

ELEMENT SELECTION GUIDE

Frequency Range	Forward Power Range	Reflected Power Range	Forward Element	Reflected Element
2-30 MHz	1.25 to 50 W 12.5 to 500 W	125 mW to 5 W 1.25 to 50 W	DPM-50H DPM-500H	DPM-5H DPM-50H
25-60 MHz	1.25 to 50 W 12.5 to 500 W	125 mW to 5 W 1.25 to 50 W	DPM-50A DPM-500A	DPM-5A DPM-50A
50-125 MHz	1.25 to 50 W 12.5 to 500 W 25 to 1.0 kW	125 mW to 5 W 1.25 to 50 W 25 to 100 W	DPM-50B DPM-500B DPM-1000B	DPM-5B DPM-50B DPM-100B
100-250 MHz	1.25 to 50 W 12.5 to 500 W 62.5 to 2.5 kW	125 mW to 5 W 1.25 to 50 W 6.25 to 250 W	DPM-50C DPM-500C DPM-2500C	DPM-5C DPM-50C DPM-250C
200-500 MHz	125 mW to 5 W 1.25 to 50 W 12.5 to 500 W	12.5 mW to 500 mW 125 mW to 5 W 1.25 to 50 W	DPM-5D DPM-50D DPM-500D	DPM-5D DPM-5D DPM-50D
400-960 MHz	125 mW to 5 W 1.25 to 50 W 2.5 to 100 W 12.5 to 500 W 25 to 1.0 kW	12.5 mW to 500 mW 125 mW to 5 W 250 mW to 10 W 1.25 to 50 W 2.5 to 100 W	DPM-5E DPM-50E DPM-100E DPM-500E DPM-1000E	DPM-5E DPM-5E DPM-10E DPM-50E DPM-100E
950-1260 MHz	125 mW to 5 W 1.25 to 50 W	12.5 mW to 500 mW 125 mW to 5 W	DPM-5J DPM-50J	DPM-5J DPM-5J
1100-1800 MHz	125 mW to 5 W 1.25 to 50 W	12.5 mW to 500 mW 125 mW to 5 W	DPM-5K DPM-50K	DPM-5K DPM-5K
1700-1990 MHz	125 mW to 5 W 1.25 to 50 W 12.5 to 500 W	125 mW to 500 W 125 mW to 5 W 12.5 to 500 W	DPM-5L1 DPM-50L1 DPM-500L1	DPM-5L1 DPM-5L1 DPM-50L1
1900-2200 MHz	125 mW to 5 W 1.25 to 50 W	12.5 mW to 500 mW 125 mW to 5 W	DPM-5L2 DPM-50L2	DPM-5L2 DPM-5L2
2200-2300 MHz	125 mW to 5 W 625 mW to 25 W	12.5 mW to 500 mW 6.25 mW to 2.5 W	DPM-5M DPM-25M	DPM-5M DPM-25M
2300-2500 MHz	125 mW to 5 W	12.5 mW to 500 mW	DPM-5N	DPM-5N
2500-2700 MHz	125 mW to 5 W	12.5 mW to 500 mW	DPM-5R	DPM-5R

COMPATIBLE DEVICES

5010B U5000-EX
5000-XT
SA-1700 EXP
SA-2500 EX
SA-6000 EX
SH-36S
SH-361S
SH-362
SH-362S

5014 5000-XT
VPM3
SA-3600 XT
SA-6000 XT
SiteHawk
RF Meter App

