

MODEL # BR-160
CUTTING CHART
(CUT WHIP FROM BOTTOM)

FREQUENCY MHz	WHIP LENGTH MM	WHIP LENGTH INCHES
144	1240	48 13/16
146	1200	47 1/4
148	1180	46 7/16
150	1165	45 7/8
152	1155	45 1/2
154	1135	44 11/16
156	1115	43 7/8
158	1097	43 3/16
160	1080	42 1/2
162	1060	41 3/4
164	1040	40 15/16
166	1020	40 3/16
168	1005	39 9/16
170	975	38 3/8
172	963	37 15/16
174	952	37 1/2

WHIP LENGTH WITH OPTIONAL # 1214 SPRING

FREQUENCY MHz	WHIP LENGTH MM	WHIP LENGTH INCHES
138	1240	48 13/16
140	1215	47 13/16
142	1190	46 7/8
144	1175	46 1/4
146	1143	45
148	1120	44 1/16
150	1102	43 3/8
152	1085	42 11/16
154	1070	42 1/8
156	1050	41 5/16
158	1025	40 3/8
160	1005	39 9/16
162	980	38 9/16
164	960	37 13/16
166	935	36 13/16
168	917	36 1/8
170	895	35 1/4
172	875	34 7/16
174	860	33 7/8

Tram-Browning, Inc.
PO Box 5056
Edmond, OK 73083 USA